



LUND UNIVERSITY

Design of multimode multiband antennas for MIMO terminals using characteristic mode analysis

Miers, Zachary; Lau, Buon Kiong

Published in:
IEEE International Symposium on Antennas and Propagation, 2014

DOI:
[10.1109/APS.2014.6905040](https://doi.org/10.1109/APS.2014.6905040)

2014

Document Version:
Peer reviewed version (aka post-print)

[Link to publication](#)

Citation for published version (APA):
Miers, Z., & Lau, B. K. (2014). Design of multimode multiband antennas for MIMO terminals using characteristic mode analysis. In *IEEE International Symposium on Antennas and Propagation, 2014* (pp. 1429-1430). IEEE - Institute of Electrical and Electronics Engineers Inc.. <https://doi.org/10.1109/APS.2014.6905040>

Total number of authors:
2

General rights

Unless other specific re-use rights are stated the following general rights apply:
Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

Read more about Creative commons licenses: <https://creativecommons.org/licenses/>

Take down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

LUND UNIVERSITY

PO Box 117
221 00 Lund
+46 46-222 00 00

Design of Multimode Multiband Antennas for MIMO Terminals using Characteristic Mode Analysis

Zachary Miers and Buon Kiong Lau

Department of Electrical and Information Technology
Lund University
223 63 Lund, Sweden
Zachary.Miers@eit.lth.se

Abstract—Characteristic mode analysis provides unparalleled insights into designing high performance multiple-input multiple-output (MIMO) terminal antennas at frequencies where the antenna elements are constrained to be electrically small. Conventionally, an electrically small single-antenna utilizes the fundamental characteristic mode of the terminal chassis to obtain sufficient bandwidth while maintaining high radiation efficiency. However, modern MIMO terminals require two or more antennas per frequency band, and they tend to excite the same fundamental chassis mode, resulting in severe coupling, correlation, and poor overall system performance. Recently, characteristic mode analysis of the chassis is proposed to design highly efficient multimode multiband MIMO antennas with significant bandwidth using electrically small feed elements. Two distinct and excitable characteristic modes were created at frequencies above and below 1 GHz, for a typical smartphone's form factor. This paper provides an overview of the method and highlights its versatility for practical implementation in standard plastic cased smartphones as well as in the popular metal-bezeled smartphones, with only minor modifications to the chassis.

I. INTRODUCTION

To realize high data rates with multiple-input multiple-output (MIMO) technology, Long Term Evolution (LTE) mandates the implementation of two or more antennas in mobile terminals per operating frequency band. Moreover, optimal MIMO performance requires the multi-antennas to be highly efficient and uncorrelated with one another.

The Theory of Characteristic Modes (TCM) [1] presents unique insights into designing highly efficient and uncorrelated antennas on a single terminal chassis. Each individual characteristic mode as extracted from this theory can be defined as an independent uncorrelated antenna radiation mode. If any given mode has a low enough characteristic eigenvalue, a feed can be designed to excite that particular antenna mode on the given structure [2]. Often an electrically compact structure (e.g., a smartphone at LTE700) will not support the feeding of multiple modes with a low enough characteristic eigenvalue over a significant bandwidth. Utilizing the technique described in [2] and [3], it is possible to decrease the characteristic eigenvalue of a mode on a given structure so that multiple modes with significant bandwidth are excitable at frequencies where the terminal chassis remains electrically compact. This is accomplished through minor, and industry-acceptable, chassis modifications [3]. Furthermore, to support multiband resonances, the modified structure's characteristic

near-fields and currents around the antenna feeds can then be correlated with higher frequency characteristic modes. Correlated higher frequency modes can then be shifted through a further slight modification of the chassis and excited using the low frequency feeds [2].

In this paper, we summarize the multiband, uncorrelated antenna design method as applied to two significantly different terminal chassis, i.e., a standard plastic encapsulated single PCB chassis [2] as well as the recently popular metal-bezel equipped chassis [1]. Both chassis were designed to support multiple antennas with multiband performance. These antennas were designed, simulated, and measured to have total antenna efficiencies of above -2dB and envelope correlation coefficients (ECC) of below 0.1 in all bands [2], [1].

II. MULTI-ANTENNA DESIGN

In [2], the chassis of a modern smartphone with the dimensions of 130 mm × 66 mm was designed using TCM to provide two resonant characteristic modes (CM) at frequencies above and below 1 GHz. The standard unmodified flat chassis only supports one resonant characteristic mode below 1 GHz, as can be seen in Fig. 1. In an effort to attain more than one resonant mode below 1 GHz, the structure must be modified. There are many ways to change a flat chassis which will result in different CMs. However, by analyzing the original characteristic currents, and near-fields, antenna matching techniques can be used to modify the chassis and help increase the resonance of non-resonant modes. The chassis only supports two modes with a characteristic eigenvalue (λ) between ± 15 below 1 GHz. λ_1 is the fundamental mode with dipole-like currents along the length of the chassis, λ_2 supports currents resembling those of a short, fat dipole along the width of the chassis. Based on standard antenna design techniques, it is reasonable to load the longer ends of the chassis with strips of metal to increase the capacitance of the λ_2 current distribution and thus bring this mode into resonance. The metal strips reduced the characteristic eigenvalue of the non-resonant dipole-like currents running along the width of the chassis. This minor modification changed the CMs of the structure to support the two resonant modes λ_1 and λ_2 . The modified λ_1 and λ_2 were fed using a standard capacitive coupling element along the top end of the chassis and a direct current feed attached to one of the two capacitive loading strips, respectively (see Fig. 2(a)).

