



# LUND UNIVERSITY

## Control of Systems with Uncertain Parameters

Åström, Karl Johan

1976

*Document Version:*

Publisher's PDF, also known as Version of record

[Link to publication](#)

*Citation for published version (APA):*

Åström, K. J. (1976). *Control of Systems with Uncertain Parameters*. (Technical Reports TFRT-7115). Department of Automatic Control, Lund Institute of Technology (LTH).

*Total number of authors:*

1

### General rights

Unless other specific re-use rights are stated the following general rights apply:

Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

Read more about Creative commons licenses: <https://creativecommons.org/licenses/>

### Take down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

LUND UNIVERSITY

PO Box 117  
221 00 Lund  
+46 46-222 00 00

CONTROL OF SYSTEMS WITH UNCERTAIN  
PARAMETERS

K.J. ÅSTRÖM

Department of Automatic Control  
Lund Institute of Technology  
January 1977

Dokumentutgivare  
Lund Institute of Technology  
Handläggare Dept of Automatic Control  
06T0  
Författare  
R8J0 Aström

Dokumentnamn  
REPOR  
Utgivningsdatum  
06T4 1977

Dokumentbeteckning  
LUTFD2/(T67115)/1-009/(1977)  
Ärendebeteckning  
06T6

10T4

Dokumenttitel och undertitel

18T0  
Control of Systems with Uncertain Parameters

Referat (sammandrag)

26T0  
The formulae for linear quadratic control of a system with uncertain parameters are derived in this note. The results are of interest in order to take uncertainties into account in computer aided design and also for adaptive control algorithms.

Referat skrivet av

A8T0 or

Förslag till ytterligare nyckelord

44T0

Klassifikationssystem och -klass(er)

50T0

Indextermer (ange källa)

52T0

Omfång

36 pages

Övriga bibliografiska uppgifter

56T2

Språk

English

Sekretessuppgifter

60T0

ISSN

60T4

ISBN

60T6

Dokumentet kan erhållas från

Department of Automatic Control  
Lund Institute of Technology  
P O Box 725, S-220 07 LUND 7, Sweden

Mottagarens uppgifter

62T4

Pris

10.- Sw Kr

Blankett LU 11:25 1976-07

CONTROL OF SYSTEMS WITH UNCERTAIN PARAMETERS

K.J. Åström

# CONTROL OF SYSTEMS WITH UNCERTAIN PARAMETERS

K J Åström

## Abstract

The formulae for linear quadratic control of a system with uncertain parameters are derived in this note. The results are of interest in order to take uncertainties into account in computer aided design and also for adaptive control algorithms.

## Contents

1. INTRODUCTION
2. PROBLEM STATEMENT
3. MAIN RESULT
4. AN EXAMPLE
5. REFERENCES

## 1. INTRODUCTION

This note considers a linear quadratic problem where the parameters of the system model are random variables. The criterion is to minimize the expected loss where the expectation is taken both with respect to process and measurement disturbances and with respect to parameter uncertainties. The solution of the problem is of interest in order to evaluate the effects of uncertainties in design of control laws for systems with uncertain parameters and for adaptive control. Results of this type was derived for single-input single-output systems using transfer function representations in Wieslander and Wittenmark (1971). The state-space formulas which are simpler were used in Peterka and Åström (1973).

## 2. PROBLEM STATEMENT

Consider the system

$$x(t+1) = \Phi x(t) + \Gamma u(t) + e(t) \quad (1)$$

where  $\{e(t)\}$  is a sequence of random vectors with zero mean values and covariances  $R_1$ . Assume that the parameters  $\Phi$  and  $\Gamma$  are random variables with known mean values and known covariances. The elements of  $\Phi$  and  $\Gamma$  are uncorrelated with  $\{e(t)\}$ . Assume that the state variable  $x$  can be measured without error. Determine a control strategy such that the criterion

$$E \left[ \sum_{k=0}^N x^T(k) Q_1 x(k) + u^T(k) Q_2 u(k) \right] \quad (2)$$

is minimal. The matrices  $Q_1$  and  $Q_2$  are assumed known. The matrices  $\Phi$  and  $\Gamma$  have mean values

$$\begin{aligned} E \Phi &= \hat{\Phi} \\ E \Gamma &= \hat{\Gamma} \end{aligned} \quad (3)$$

To express the uncertainties of  $\Phi$  and  $\Gamma$ . We introduce

$$\begin{aligned} \Phi &= [\varphi_1 \quad \varphi_2 \quad \dots \quad \varphi_n] \\ \Gamma &= [\gamma_1 \quad \gamma_2 \quad \dots \quad \gamma_n] \end{aligned} \quad (4)$$

The uncertainties are defined by

$$\begin{aligned} R_{\varphi_i \varphi_j} &= E [\varphi_i - \hat{\varphi}_i] [\varphi_j - \hat{\varphi}_j] = \text{cov} [\varphi_i, \varphi_j] \\ R_{\varphi_i \gamma_j} &= E [\varphi_i - \bar{\varphi}_i] [\gamma_j - \hat{\gamma}_j] = \text{cov} [\varphi_i, \gamma_j] \\ R_{\gamma_i \gamma_j} &= E [\gamma_i - \hat{\gamma}_i] [\gamma_j - \hat{\gamma}_j] = \text{cov} [\gamma_i, \gamma_j] \end{aligned} \quad (5)$$

### 3. MAIN RESULT

To solve the problem we proceed in the usual manner using Dynamic Programming. Assume that the minimum exists and introduce

$$V(x, t) = \min_u E \left[ \sum_{k=t}^N x^T(k) Q_1 x(k) + u^T(k) Q_2 u(k) \right] \quad (6)$$

where  $E$  denotes the conditional expectation given  $x(t)$ .

We have

$$V(x, N) = x^T Q_1 x \quad (7)$$

It will now be shown by induction that  $V(x, t)$  is a quadratic form, i.e.

$$V(x, t) = x^T S(t) \psi + \alpha(t) \quad (8)$$

This is apparently true for  $t = N$  with

$$\begin{cases} S(N) = Q_1 \\ \alpha(N) = 0 \end{cases}$$

Assuming that (8) holds for  $t+1$  it will be shown by induction that it holds also for  $t$ . We have

$$V(x, t) = \min_u E \left[ x^T(t) Q_1 x(t) + u^T(t) Q_2 u(t) + V[x(t+1), t+1] \right] \quad (9)$$

Drop the argument  $t$  in  $x(t)$  to simplify the writing, introduce (1) and (8) into (6). Then

$$\begin{aligned} V(x, t) &= \min_u E \left[ x^T Q_1 x + u^T Q_2 u + V(\Phi x + \Gamma u + e, t+1) \right] = \\ &= \min_u E \left[ x^T Q_1 x + u^T Q_2 u + (\Phi x + \Gamma u + e)^T S(t+1) (\Phi x + \Gamma u + e) + \alpha(t+1) \right] = \\ &= \min_u \left[ x^T Q_1 x + u^T Q_2 u + E x^T \Phi^T S(t+1) \Phi x + E x^T \Phi^T S(t+1) \Gamma u + \right. \\ &\quad \left. + E u^T \Gamma^T S(t+1) \Phi x + E u^T \Gamma^T S(t+1) \Gamma u + \text{tr } S(t+1) R_1 + \alpha(t+1) \right] \end{aligned} \quad (10)$$



To proceed it is now necessary to evaluate

$$E \mathbf{x}^T \Phi^T S(t+1) \Phi \mathbf{x}$$

$$E \mathbf{x}^T \Phi^T S(t+1) \Gamma \mathbf{u}$$

$$E \mathbf{u}^T \Gamma^T S(t+1) \Gamma \mathbf{u}$$

This is simple in principle but messy in detail unless we are careful about our notation. Equation (4) gives

$$\Phi^T S \Phi = \begin{bmatrix} \varphi_1^T \\ \varphi_2^T \\ \vdots \\ \varphi_n^T \end{bmatrix} S [\varphi_1 \ \varphi_2 \ \dots \varphi_n] = \begin{bmatrix} \varphi_1^T S \varphi_1 & \varphi_1^T S \varphi_2 & \dots & \varphi_1^T S \varphi_n \\ \varphi_2^T S \varphi_1 & \varphi_2^T S \varphi_2 & \dots & \varphi_2^T S \varphi_n \\ \vdots & \vdots & \ddots & \vdots \\ \varphi_n^T S \varphi_1 & \varphi_n^T S \varphi_2 & \dots & \varphi_n^T S \varphi_n \end{bmatrix}$$

Taking mathematical expectations we find

$$E \Phi^T S \Phi = \hat{\Phi}^T S \hat{\Phi} + A_1(S) \quad (11)$$

$$A_1(S) = \begin{bmatrix} \text{tr } S R_{\varphi_1 \varphi_1} & \text{tr } S R_{\varphi_2 \varphi_1} & \dots & \text{tr } S R_{\varphi_n \varphi_1} \\ \text{tr } S R_{\varphi_1 \varphi_2} & \text{tr } S R_{\varphi_2 \varphi_2} & \dots & \text{tr } S R_{\varphi_n \varphi_2} \\ \vdots & \vdots & \ddots & \vdots \\ \text{tr } S R_{\varphi_1 \varphi_n} & \text{tr } S R_{\varphi_2 \varphi_n} & \dots & \text{tr } S R_{\varphi_n \varphi_n} \end{bmatrix} \quad (12)$$

$$E \varphi_i^T S \varphi_j = E \varphi_j^T S \varphi_i = E \text{tr } \varphi_j^T S \varphi_i = E \text{tr } S \varphi_i \varphi_j^T = \text{tr } S R_{\varphi_i \varphi_j}$$

which implies

$$\text{tr } S R_{\varphi_j \varphi_i} = \text{tr } R_{\varphi_j \varphi_i} S = \text{tr } S R_{\varphi_i \varphi_j} = \text{tr } R_{\varphi_i \varphi_j} S \quad (14)$$

Similarly we find

$$E \Phi^T S \Gamma = \hat{\Phi}^T S \hat{\Gamma} + A_2(S) \quad (15)$$

$$A_2(S) = \begin{pmatrix} \text{tr } SR_{\gamma_1 \varphi_1} & \text{tr } SR_{\gamma_2 \varphi_1} & \dots & \text{tr } SR_{\gamma_p \varphi_1} \\ \text{tr } SR_{\gamma_1 \varphi_2} & \text{tr } SR_{\gamma_2 \varphi_2} & \dots & \text{tr } SR_{\gamma_p \varphi_2} \\ \vdots & & & \\ \text{tr } SR_{\gamma_1 \varphi_n} & \text{tr } SR_{\gamma_2 \varphi_n} & \dots & \text{tr } SR_{\gamma_p \varphi_n} \end{pmatrix} \quad (16)$$

$$E \Gamma^T S \Gamma = \hat{\Gamma}^T S \hat{\Gamma} + A_3(S) \quad (17)$$

$$A_3(S) = \begin{pmatrix} \text{tr } SR_{\gamma_1 \gamma_1} & \text{tr } SR_{\gamma_1 \gamma_2} & \dots & \text{tr } SR_{\gamma_1 \gamma_p} \\ \text{tr } SR_{\gamma_2 \gamma_1} & \text{tr } SR_{\gamma_2 \gamma_2} & \dots & \text{tr } SR_{\gamma_2 \gamma_p} \\ \vdots & & & \\ \text{tr } SR_{\gamma_p \gamma_1} & \text{tr } SR_{\gamma_p \gamma_2} & \dots & \text{tr } SR_{\gamma_p \gamma_p} \end{pmatrix} \quad (18)$$

Introducing (10), (15) and (17) into (8) we get

$$\begin{aligned} V(x, t) = \min_u \{ & u^T [Q_2 + \hat{\Gamma}^T S(t+1) \hat{\Gamma} + A_3(S(t+1))] u + \\ & + u^T [\hat{\Gamma}^T S(t+1) \hat{\Phi} + A_2^T(S(t+1))] x + \\ & + x^T [\hat{\Phi}^T S(t+1) \hat{\Gamma} + A_2(S(t+1))] u + \\ & + x^T [Q_1 + \hat{\Phi}^T S(t+1) \hat{\Phi} + A_1(S(t+1))] + \\ & + \text{tr } S(t+1) R_1 + \alpha(t+1) \} \end{aligned}$$

Summarizing the results we find

#### THEOREM

The optimal control strategy is given by

$$u(t) = -L x(t)$$

where

$$L = [Q_2 + \hat{\Gamma}^T S(t+1) \hat{\Gamma} + A_3(S(t+1))]^{-1} [\hat{\Gamma}^T S(t+1) \hat{\Phi} + A_2^T(S(t+1))]$$

and

$$\begin{aligned}
 S(t) &= \hat{\Phi}^T S(t+1) \hat{\Phi} + Q_1 - L^T [Q_2 + \hat{\Gamma}^T S(t+1) \hat{\Gamma} + A_3(S(t+1))] L + A_1(S(t+1)) = \\
 &= \hat{\Phi}^T S(t+1) [\hat{\Phi} - \hat{\Gamma} L] + Q_1 + A_1(S(t+1)) - A_2(S(t+1)) L = \\
 &= (\hat{\Phi} - \hat{\Gamma} L)^T S(t+1) (\hat{\Phi} - \hat{\Gamma} L) + Q_1 + A_1 + L^T Q_2 L - A_2 L - L^T A_2^T
 \end{aligned}$$

where

$$A_1(S) = \begin{pmatrix} \text{tr } R_{\varphi_1 \varphi_1} S & \text{tr } R_{\varphi_1 \varphi_2} S & \dots & \text{tr } R_{\varphi_1 \varphi_n} S \\ \text{tr } R_{\varphi_2 \varphi_1} S & \text{tr } R_{\varphi_2 \varphi_2} S & \dots & \text{tr } R_{\varphi_2 \varphi_n} S \\ \vdots & & & \\ \text{tr } R_{\varphi_n \varphi_1} S & \text{tr } R_{\varphi_n \varphi_2} S & \dots & \text{tr } R_{\varphi_n \varphi_n} S \end{pmatrix}$$

$$A_2(S) = \begin{pmatrix} \text{tr } R_{\varphi_1 \gamma_1} S & \text{tr } R_{\varphi_1 \gamma_2} S & \dots & \text{tr } R_{\varphi_1 \gamma_p} S \\ \text{tr } R_{\varphi_2 \gamma_1} S & \text{tr } R_{\varphi_2 \gamma_2} S & \dots & \text{tr } R_{\varphi_2 \gamma_p} S \\ \vdots & & & \\ \text{tr } R_{\varphi_n \gamma_1} S & \text{tr } R_{\varphi_n \gamma_2} S & \dots & \text{tr } R_{\varphi_n \gamma_p} S \end{pmatrix}$$

$$A_3(S) = \begin{pmatrix} \text{tr } R_{\gamma_1 \gamma_1} S & \text{tr } R_{\gamma_1 \gamma_2} S & \dots & \text{tr } R_{\gamma_1 \gamma_p} S \\ \text{tr } R_{\gamma_2 \gamma_1} S & \text{tr } R_{\gamma_2 \gamma_2} S & \dots & \text{tr } R_{\gamma_2 \gamma_p} S \\ \vdots & & & \\ \text{tr } R_{\gamma_p \gamma_1} S & \text{tr } R_{\gamma_p \gamma_2} S & \dots & \text{tr } R_{\gamma_p \gamma_p} S \end{pmatrix}$$

where  $\varphi_i$  and  $\gamma_i$  are defined by (4) and  $R_{\varphi\gamma}$  by (5)

## 4. AN EXAMPLE

The equations become especially simple in the case of systems on companion form. Assume

$$\Phi = \begin{pmatrix} -a_1 & 1 & 0 & \dots & 0 \\ -a_2 & 0 & 1 & \dots & 0 \\ \vdots & & & & \\ -a_n & 0 & 0 & \dots & 0 \end{pmatrix}, \quad \Gamma = \begin{pmatrix} b_1 \\ b_2 \\ \vdots \\ b_n \end{pmatrix}$$

In this case we get

$$A_1 = \begin{pmatrix} \text{tr } SR_{\varphi_1 \varphi_1} & 0 & \dots & 0 \\ 0 & 0 & \dots & 0 \\ \vdots & & & \\ 0 & 0 & \dots & 0 \end{pmatrix}$$

$$A_2 = \begin{pmatrix} \text{tr } SR_{\gamma_1 \varphi_1} \\ 0 \\ \vdots \\ 0 \end{pmatrix} \quad A_2^T = ( \text{tr } SR_{\gamma_1 \varphi_1} \quad 0 \quad \dots \quad 0 )$$

$$A_3 = \text{tr } SR_{\gamma_1 \gamma_1}$$

## 5. REFERENCES

Wieslander, J and Wittenmark, B:

An Approach to Adaptive Control Using Real Time Identification. Automatica 7 (1971) 211-217.

Peterka, V and Åström, K J:

Control of Multivariable Systems with Unknown but Constant Parameters. Proc 3rd IFAC Symposium on Identification and System Parameter Estimation, The Hague, 1973.