LUND UNIVERSITY

A genie-aided detector with a probabilistic description of the side information

Eriksson, Håkan B.; Ödling, Per; Koski, Timo; Börjesson, Per Ola

Published in:
[Host publication title missing]

DOI:
[10.1109/ISIT.1995.550319](https://doi.org/10.1109/ISIT.1995.550319)

1995

[Link to publication](#)

Citation for published version (APA):
Eriksson, H. B., Ödling, P., Koski, T., & Börjesson, P. O. (1995). A genie-aided detector with a probabilistic description of the side information. In *[Host publication title missing]* (pp. 332)
<https://doi.org/10.1109/ISIT.1995.550319>

Total number of authors:
4

General rights

Unless other specific re-use rights are stated the following general rights apply:
Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.

- Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
- You may not further distribute the material or use it for any profit-making activity or commercial gain
- You may freely distribute the URL identifying the publication in the public portal

Read more about Creative commons licenses: <https://creativecommons.org/licenses/>

Take down policy

If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

LUND UNIVERSITY

PO Box 117
221 00 Lund
+46 46-222 00 00

A Genie-Aided Detector with a Probabilistic Description of the Side Information

Håkan B. Eriksson¹ Per Ödling¹ Timo Koski² Per Ola Börjesson¹

¹ Division of Signal Processing, Luleå University of Technology, S-971 87 Luleå, Sweden

² Department of Mathematics, Royal Institute of Technology, S-100 44 Stockholm, Sweden

Abstract—Building on Forney's concept of the genie [4], [5], and introducing the idea of an *explicit statistical description* of the side information provided to the genie-aided detector, we develop a generic tool for derivation of lower bounds on the bit-error rate of any actual receiver [3]. With this approach, the side information statistics become *design parameters*, which may be chosen to give the resulting bound a desired structure. To illustrate this, we choose statistics in order to obtain a special case: the lower bound derived by Mazo [6]. The statistical description of the side information makes the lower bounding a transparent application of Bayesian theory.

I. INTRODUCTION

The idea of a *good genie* with a corresponding *genie-aided detector* (GAD) has, in particular, often been used to determine a lower performance bound for the probability of bit-error [1], [2], [3], [4], [5]. The GAD has access to more information than any actual detector: it has access to the side information supplied by the genie and is expected to handle all information *optimally*. Because of this, it is argued, it cannot have a worse performance than any detector working without the side information. However, in order that optimal processing of the side information be well-defined in the sense of Bayesian detection theory, an explicit (statistical) description of the side information is required. This paper introduces such a representation of the genie, augmenting the foundational ideas of Forney's work in [4], [5]. Our aim is to introduce the side information supplied by the genie as the output of a "side information channel" parallel to the original channel and governed by a *probabilistic rule* with free parameters.

II. THE SIDE INFORMATION CHANNEL

Consider a transmission system where binary data is sent through a discrete-time, additive Gaussian channel with intersymbol interference, and where additional side information is carried to the detector through a parallel channel (representing the genie).

We discuss the detection of bit number k in the important special case when the side information consists of a pair of sequences and one of the sequences is equal to the transmitted sequence, cf. [4], [5]. Define $\mathcal{C}_k^+$ and $\mathcal{C}_k^-$ as the sets of sequences with the bit in position k as $+1$ and -1 , respectively, and denote the side information with z and its outcome with ζ . Let ζ consist of pairs in $\mathcal{C}_k^+ \times \mathcal{C}_k^-$ of the form $\zeta_{i,j} \triangleq (\beta_i^+, \beta_j^-)$, for $1 \leq i, j \leq 2^{N-1}$. With the transmitted sequence being β , let the additional sequence be chosen at random among the sequences differing from β in bit k , according to the *known, probabilistic* transition

rule:

$$\Pr\{z = \zeta_{i,j} | \mathbf{b} = \beta\} = \begin{cases} p(j|i) & \text{if } \beta = \beta_i^+ \in \mathcal{C}_k^+ \\ q(i|j) & \text{if } \beta = \beta_j^- \in \mathcal{C}_k^- \\ 0 & \text{otherwise.} \end{cases}$$

Hence, the properties of the genie, or equivalently, the properties of the output of the side information channel, are defined by the statistics (or transition probabilities) $p(j|i)$ and $q(i|j)$.

III. THE GENIE-AIDED DETECTOR

With the complete statistical description of the transmission system, including a set of transition probabilities, the GAD with minimum bit-error probability is derived in terms of a binary Bayesian hypothesis test. By evaluating the performance of this GAD, a lower bound on the probability of bit-error of any detector, with or without access to the side information, is obtained as

$$P_{\text{BER},k} \geq \frac{\sum_{i,j} Q\left(\frac{d_{i,j}}{2} + \frac{\ln \gamma_{i,j}}{d_{i,j}}\right) q(i|j) \Pr\{\mathbf{b} = \beta_j^-\} + \sum_{i,j} Q\left(\frac{d_{i,j}}{2} - \frac{\ln \gamma_{i,j}}{d_{i,j}}\right) p(j|i) \Pr\{\mathbf{b} = \beta_i^+\}}{\sum_{i,j} Q\left(\frac{d_{i,j}}{2} + \frac{\ln \gamma_{i,j}}{d_{i,j}}\right) q(i|j) \Pr\{\mathbf{b} = \beta_j^-\} + \sum_{i,j} Q\left(\frac{d_{i,j}}{2} - \frac{\ln \gamma_{i,j}}{d_{i,j}}\right) p(j|i) \Pr\{\mathbf{b} = \beta_i^+\}},$$

where $d_{i,j}$ is the Euclidian distance between β_i^+ and β_j^- ,

$$\gamma_{i,j} = \frac{q(i|j) \Pr\{\mathbf{b} = \beta_j^-\}}{p(j|i) \Pr\{\mathbf{b} = \beta_i^+\}}$$

and $Q(x) \triangleq (1/\sqrt{2\pi}) \int_x^{+\infty} e^{-t^2/2} dt$.

The transition probabilities $\{p(j|i), q(i,j)\}$ are free parameters which can be chosen to optimize the performance of the GAD. They might for example be chosen to make the corresponding bound tight, or to give the bound a simple structure. We choose several sets of transition probabilities as examples in order to discuss the properties of their respective performance bounds. In this, we also discuss the relation of the attainable performance bounds to the works by Forney [4], [5] and Mazo [6].

REFERENCES

- [1] T. Aulin, "Genie-aided sequence detection under mismatch," In *Proc. ISITA '94*, pp. 869–873, Sydney, Australia, Nov. 1994.
- [2] R.E. Blahut, *Digital Transmission of Information*. New York: Addison-Wesley Publ. Comp., 1990.
- [3] H.B. Eriksson, P. Ödling, T. Koski and P.O. Börjesson "A genie-aided detector based on a probabilistic description of the side information," Subm. to *IEEE Trans. Inf. Th.*, May 1995.
- [4] G.D. Forney, "Lower bounds on error probability in the presence of large intersymbol interference," *IEEE Trans. Commun.*, vol. 20, no. 1, pp. 76–77, Feb. 1972.
- [5] G.D. Forney, "Maximum likelihood sequence estimation of digital sequences in the presence of intersymbol interference," *IEEE Trans. Inf. Th.*, vol. 18, no. 3, pp. 363–378, May 1972.
- [6] J.E. Mazo, "Faster-than-Nyquist-signaling," *The Bell System Technical Journal*, vol. 54, Oct. 1975, pp. 1451–1462.