LUND UNIVERSITY

Propagation inside a bianisotropic waveguide as an evolution problem

Ioannidis, Andreas; Kristensson, Gerhard; Sjöberg, Daniel

2012

Link to publication

Citation for published version (APA):
Ioannidis, A., Kristensson, G., & Sjöberg, D. (2012). *Propagation inside a bianisotropic waveguide as an evolution problem.* Abstract from Modern Mathematical Methods in Science and Technology, Kalamata, Greece.

Total number of authors:
3

General rights
Unless other specific re-use rights are stated the following general rights apply:
Copyright and moral rights for the publications made accessible in the public portal are retained by the authors and/or other copyright owners and it is a condition of accessing publications that users recognise and abide by the legal requirements associated with these rights.
• Users may download and print one copy of any publication from the public portal for the purpose of private study or research.
• You may not further distribute the material or use it for any profit-making activity or commercial gain
• You may freely distribute the URL identifying the publication in the public portal

Read more about Creative commons licenses: https://creativecommons.org/licenses/

Take down policy
If you believe that this document breaches copyright please contact us providing details, and we will remove access to the work immediately and investigate your claim.

LUND UNIVERSITY

PO Box 117
221 00 Lund
+46 46-222 00 00

PROPAGATION INSIDE A BIANISOTROPIC WAVEGUIDE AS AN EVOLUTION PROBLEM

A. D. IOANNIDIS, G. KRISTENSSON AND D. SJÖBERG

Abstract

The free source Maxwell system for the bianisotropic medium, in a fixed frequency $\omega \geqslant 0$ and with time convention $\mathrm{e}^{-\mathrm{i}\omega t}$, is represented by the equation

$$\nabla \times \mathsf{J}\mathsf{e} = \mathrm{i}\omega \mathsf{M}\mathsf{e} \tag{0.1}$$

where $\mathsf{e} := (\boldsymbol{E}, \boldsymbol{H})^{\mathrm{T}}$ is the electromagnetic (E/M) field; it is defined in a domain $\Omega \subset \mathbb{R}^3$, depend on ω and take values in $\mathbb{C}^6$. We denote

$$\mathsf{J} := \begin{bmatrix} 0 & -I_3 \\ I_3 & 0 \end{bmatrix}$$

The matrix

$$\mathsf{M} := \begin{bmatrix} \boldsymbol{\varepsilon} & \boldsymbol{\xi} \\ \boldsymbol{\zeta} & \boldsymbol{\mu} \end{bmatrix}$$

characterizes the medium inside Ω and its entries are complex functions of the frequency ω and the position $\boldsymbol{r} \in \Omega$. The Gauss law implies that

$$\nabla \cdot \mathsf{M}\mathsf{e} = 0 \tag{0.2}$$

Assume that the boundary $\Gamma := \partial\Omega$ is smooth enough; usually Lipschitz is sufficient for most of the applications. Let $\hat{\boldsymbol{n}}$ be the exterior normal to Γ. For a wide class of boundaries, metallic for example, the perfect electric conductor (PEC) boundary condition for the electric field, $\hat{\boldsymbol{n}} \times \boldsymbol{E} = \boldsymbol{0}$ on Γ, applies.

Let now $\boldsymbol{A} = (A_x, A_y, A_z)^T$ be a vector field in Ω; it can be represented as $\boldsymbol{A} = (\boldsymbol{A}_\perp, A_z)^{\mathrm{T}}$ where $\boldsymbol{A}_\perp := A_x\hat{\mathbf{x}} + A_y\hat{\mathbf{y}}$ is the transverse and A_z the longitudinal part. It is easily seen that the *curl* operator reads

$$\nabla \times \boldsymbol{A} = \begin{bmatrix} W & 0 \\ 0 & 0 \end{bmatrix} \partial_z \begin{pmatrix} \boldsymbol{A}_\perp \\ A_z \end{pmatrix} - \begin{bmatrix} 0 & W\nabla_\perp \\ \nabla_\perp \cdot W & 0 \end{bmatrix} \begin{pmatrix} \boldsymbol{A}_\perp \\ A_z \end{pmatrix} \tag{0.3}$$

where

$$W := \begin{bmatrix} 0 & -1 \\ 1 & 0 \end{bmatrix} = \hat{\mathbf{z}} \times I_3$$

and $\nabla_\perp := \partial_x\hat{\mathbf{x}} + \partial_y\hat{\mathbf{y}}$ is the formal transverse gradient.

An infinite waveguide is a cylinder

$$\Omega = \Omega_\perp \times \mathbb{R}$$

where $\Omega_\perp \subset \mathbb{R}^2$ is a domain with $\Gamma_\perp$. Observe that the wall of the waveguide is $\Gamma = \Gamma_\perp \times \mathbb{R}$ and $\hat{\boldsymbol{n}}$ coincides with its transverse part and is the exterior normal

to $\Gamma_\perp$, whereas $\hat{\boldsymbol{\tau}} := W\hat{\boldsymbol{\nu}}$ is the tangent vector. The PEC boundary condition now reads

$$\hat{\boldsymbol{\tau}} \cdot \boldsymbol{E}_\perp = 0 \quad , \quad E_z = 0 \text{ on } \Gamma \tag{0.4}$$

The fact that the longitudinal variable z runs $\mathbb{R}$ allows us to formulate the Maxwell system as an evolution equation with respect to this variable. Indeed, letting

$$C := \begin{bmatrix} 0 & W\nabla_\perp \\ \nabla_\perp \cdot W & 0 \end{bmatrix}$$

the Maxwell system is written

$$\partial_z \mathsf{V}\mathsf{e} = (\mathsf{A}_0 + \mathrm{i}\omega\mathsf{M})\mathsf{e}$$

where $\mathsf{V} := \hat{\mathbf{z}} \times \mathsf{J}$ and $\mathsf{A}_0 := C\mathsf{J}$. Define now a Hilbert space $\mathcal{X}$ of functions of the transverse variables and consider the E/M field e as vector–valued a function

$$\mathsf{e} \,:\, \mathbb{R} \ni z \mapsto \mathsf{e}(\cdot,\cdot,z) \in \mathcal{X}$$

Then A_0 can be realized as an unbounded operator in $\mathcal{X}$ and the PEC conditions are incorporated in the domain of A_0. Actually, if we separate $\mathsf{u} \in \mathcal{X}$ into "electric" and "magnetic" part

$$\mathsf{u} =: \begin{pmatrix} \mathsf{u}^e \\ \mathsf{u}^h \end{pmatrix},$$

then A_0 is given explicitly by

$$\mathsf{A}_0\mathsf{u} = \begin{pmatrix} -W\nabla_\perp \mathsf{u}_z^h \\ -\nabla_\perp \cdot W\mathsf{u}_\perp^h \\ W\nabla_\perp \mathsf{u}_z^e \\ \nabla_\perp \cdot W\mathsf{u}_\perp^e \end{pmatrix} \tag{0.5}$$

The first step is to prove that A_0 is the generator of a strongly continuous group in $\mathcal{X}$. The second is to realize Maxwell system as a perturbed abstract degenerate evolution problem

$$\mathsf{V}\mathsf{e}'(z) = (\mathsf{A}_0 + \mathrm{i}\omega\mathsf{M}(\omega))\mathsf{e}(z) \tag{0.6}$$

and apply relevant perturbation arguments in order to establish well-posedness. The research presented here implements exactly this program.

School of Computer Science, Physics and Mathematics, Linnæus University, 35195 Växjö, Sweden
E-mail address: `andreas.ioannidis@lnu.se`

Department of Electrical and Information Technology, University of Lund, P.O. Box 118, 22100 Lund, Sweden
E-mail address: {`gerhard.kristensson, daniel.sjoberg`}`@eit.lth.se`